

“KUSAM-MECO” EARTH RESISTANCE & SOIL RESISTIVITY TESTER MODEL - KM 4235ER

KUSAM-MECO has introduced new Earth Resistance & Soil Resistivity tester Model KM 4235ER for earth resistance and soil resistivity measurement. This instrument is microprocessor controlled and has auto range facility to measure earth resistance from 0 to 2000 Ω in three range i.e.: 0-200 Ω /0-200 Ω /0- 2000 Ω and earth resistivity range 0.06-6.28k Ω m / 0.62- 62.8k Ω m/ 6.28-628k Ω m. Earth resistance resolution at range 0-200 Ω is 0.01 Ω at range 0- 200 Ω 0.1 Ω and at range 0-200 Ω is 1 Ω and having accuracy + (2%rdg + 3dgts). It can measure earth voltage from 0 to 300V AC. It also has following features i.e.: Auto power off, Data hold, memory save feature up to 200 measurements, large LCD display (2 line x 16 characters), and having 2 wire test, 3 wire test, 4 wire test, automatic “c” spike check, automatic “P”. spike check facility. Distance between auxiliary earth spikes can be up to 1.0 – 50.0 m. It complies with safety standards EN61326-1, CAT IV 300V, IEC61557-1, IEC 61557-5, En61326-1. Preliminary Data It is housed in a highly insulated strong plastic case and supplied with 4 spikes, test leads, instruction manual, shoulder belt, carrying case & batteries. It is light in weight (1450 gram including batteries) and handy to carry (Size 250(L) x 190 (W) x 110(D) mm). It comes with a one year warranty. For More Details Contact : KUSAM ELECTRICAL INDUSTRIES LTD. G-17, Bharat Industrial Estate, T. J. Road, Sewree (W), Mumbai - 400015. INDIA. Sales Direct : 022- 24156638, Tel.: 022 – 27750662, 24124540, 24181649, Fax : 022 – 24149659, 27751612 Email : kusam_meco@vsnl.net, sales@kusam-meco.co.in Website : www.kusamelectrical.com ; www.kusam-meco.co.in